

# **HXP**

Mercury short-arc lamps, long life



## Product family benefits

- Very high luminance
- Elliptical reflector for efficient focusing of the light
- Long lamp life

## Product family features


- AC operation with square-wave current








# Product family datasheet





Product line drawing

Product line drawing

# Product family datasheet

#### Technical data

	Electrical data					Light technica l data	Dimensions & weight		Lifespan	Capabilities
Product description	Lamp wattage	Lamp voltage	Lamp current	Type of current	Nominal voltage	Focal length	Diameter	Length with base excl. base pins/connection	Lifespan	Cooling
HXP R 120 W/17 C <sup>1)</sup>	120 W	7095 V <sup>4)</sup>	1.5 A	AC		17.3 mm	65.0 mm	77.00 mm	2000 h	Forced
HXP R 120 W/45 C VIS <sup>1)</sup>	120 W	6090 V <sup>4)</sup>	1.4 A	AC	85.0 V	45.0 mm	67.0 mm	77.00 mm	2000 h	Forced
HXP R 120 W/45 C UV <sup>1)</sup>	120 W	6090 V <sup>4)</sup>	1.4 A	AC	85.0 V	45.0 mm	67.0 mm	77.00 mm	2000 h	Forced
HXP R 200 W/45 M <sup>2)</sup>	200 W	6096 V <sup>4)</sup>	3.4 A	AC	85.0 V	45.0 mm	67.0 mm	77.00 mm	2000 h	Forced
HXP R 206 W/45C 3)	5500 W	4885 V <sup>4)</sup>	3.4 A	AC	85.0 V	45.0 mm	67.0 mm	77.00 mm	1000 h	Forced

Product description	Burning position
HXP R 120 W/17 C <sup>1)</sup>	p20
HXP R 120 W/45 C VIS 1)	p20
HXP R 120 W/45 C UV 1)	p20
HXP R 200 W/45 M <sup>2)</sup>	p20
HXP R 206 W/45C 3)	p20

<sup>1)</sup> To be operated with PT-VIP 2AC/380 O1 DIM 120 VS25

<sup>2)</sup> To be operated with PT-VIP 4AC/380 O3 200 DIM VS50

<sup>3)</sup> To be operated with PT-VIP 4AC/380 O3 DIM 206 VS50

<sup>&</sup>lt;sup>4)</sup> Initial voltage range

## Product family datasheet

#### Safety advice

Because of their high luminance, UV radiation and high internal pressure in the hot state HXP lamps may only be operated in enclosed lamp casings specially constructed for the purpose. Mercury is released if the lamp breaks. Special safety precautions must be taken. More information is available on request or can be found in the leaflet included with the lamp or in the operating instructions.

#### Application advice

For more detailed application information and graphics please see product datasheet.

#### Disclaimer

Subject to change without notice. Errors and omission excepted. Always make sure to use the most recent release.